

**Description**

tube outside diameter: 1/2", steel, AN742 series clamp

\* Manufacturer certifications are shipped with your order FREE of charge[Order this part online](#)**Additional Information**

|                         |                             |
|-------------------------|-----------------------------|
| SKU / Model:            | AN7428                      |
| Minimum Qty (MOQ):      | 10                          |
| NSN:                    | 5340-00-200-8639            |
| ECCN:                   | EAR99                       |
| National Motor Freight: | 095190, Hardware, Noi Sub 9 |



\* See page 2 for technical characteristics

## P/N AN742-8 Specifications

|  |  |
|--|--|
| <b>Tongue Hole Type:</b>   | Round, Unthreaded  |
| <b>Overall Width:</b>  | 0.375 Inches Nominal   |
| <b>Diameter:</b>   | 0.204 Inches Nominal   |
| <b>Material Thickness:</b>                                       | 0.029 Inches Minimum And 0.036 Inches Maximum  |
| <b>Center To Center Distance Between Loop And Mounting Hole:</b> | 0.592 Inches Nominal   |
| <b>Distance From Loop Center To Tongue End:</b>                  | 0.780 Inches Nominal   |
| <b>Loop Inside Diameter:</b>                                     | 0.485 Inches Minimum And 0.515 Inches Maximum  |
| <b>Material:</b>   | Steel Comp 1006 Band Or Steel Comp 1008 Band Or Steel Comp 1009 Band Or Steel Comp 1010 Band Or Steel Comp 1012 Band Or Steel Comp 1015 Band Or Steel Comp 1017 Band |
| <b>Material Document And Classification:</b>                     | Qq-s-636 Fed Spec All Material Responses Band  |
| <b>Surface Treatment:</b>  | Cadmium Band   |
| <b>Style Designator:</b>   | Single Loop  |
| <b>Nondefinitive Spec/std Data:</b>                              | 1 Type And B Class   |

## How to Order

Order this loop clamp from our inventory online by visiting <https://military-fasteners.com/clamps/loop+clamps/AN742-8> and selecting the quantity you want then click "add to cart". Once items are in your cart you can check out [here](#) to complete your order.